



PERFORMANCE CHART FOR 4" BOREWELL SUBMERSIBLE PUMPSETS

50Hz

| PUMP + MOTOR | STAGES | CAPACITY | | | | | | | | POWER | | RATED CURRENT (A) | DIMENSIONS in 'mm' | | | APPROX. PUMPSET WEIGHT | |
|----------------------|--------|----------|-----|-----|-----|-----|-----|-----|-----|-------|------|-------------------|--------------------|------|------|------------------------|----|
| | | UK gpm | 0 | 2 | 4 | 6 | 7 | 9 | 11 | | | | 14 | Max | | | |
| | | lpm | 0 | 8 | 17 | 25 | 33 | 42 | 50 | 62 | HP | | kW | A | B | C | Kg |
| | | lps | 0 | 0.1 | 0.3 | 0.4 | 0.6 | 0.7 | 0.8 | 1.0 | | | | | | | |
| m ³ /hr | 0 | 0.5 | 1.0 | 1.5 | 2.0 | 2.5 | 3.0 | 3.7 | | | | | | | | | |
| SINGLE PHASE - 220 V | | | | | | | | | | | | | | | | | |
| SRF05/07 + FS003 | 07 | HEAD (m) | 40 | 38 | 35 | 32 | 28 | 23 | 16 | 4 | 0.5 | 0.37 | 5.0 | 926 | 386 | 540 | 26 |
| SRF05/10 + FS005 | 10 | | 57 | 54 | 50 | 45 | 40 | 32 | 22 | 6 | 0.75 | 0.55 | 6.0 | 1031 | 461 | 570 | 28 |
| SRF05/15 + FS007 | 15 | | 85 | 81 | 75 | 68 | 59 | 48 | 33 | 9 | 1.0 | 0.75 | 7.0 | 1186 | 586 | 600 | 32 |
| SRF05/22 + FS011 | 22 | | 125 | 118 | 109 | 100 | 87 | 71 | 49 | 13 | 1.5 | 1.1 | 10.0 | 1401 | 761 | 640 | 36 |
| SRF05/25 + FS015 | 25 | | 142 | 135 | 124 | 114 | 99 | 81 | 56 | 15 | 2.0 | 1.5 | 13.8 | 1516 | 836 | 680 | 39 |
| SRF05/30 + FS015 | 30 | | 171 | 161 | 149 | 136 | 119 | 97 | 67 | 18 | 2.0 | 1.5 | 13.8 | 1641 | 961 | 680 | 41 |
| SRF05/35 + FS022 | 35 | | 199 | 188 | 174 | 159 | 138 | 113 | 78 | 21 | 3.0 | 2.2 | 19.8 | 1816 | 1086 | 730 | 45 |
| SRF05/40 + FS022 | 40 | | 228 | 215 | 199 | 182 | 158 | 129 | 89 | 24 | 3.0 | 2.2 | 19.8 | 1941 | 1211 | 730 | 47 |
| SRF05/45 + FS022 | 45 | | 256 | 242 | 224 | 204 | 178 | 145 | 100 | 27 | 3.0 | 2.2 | 19.8 | 2066 | 1336 | 730 | 49 |
| THREE PHASE - 380 V | | | | | | | | | | | | | | | | | |
| SRF05/15 + FT007 | 15 | HEAD (m) | 85 | 81 | 75 | 68 | 59 | 48 | 33 | 9 | 1.0 | 0.75 | 2.7 | 1186 | 586 | 600 | 32 |
| SRF05/22 + FT011 | 22 | | 125 | 118 | 109 | 100 | 87 | 71 | 49 | 13 | 1.5 | 1.1 | 3.5 | 1381 | 761 | 620 | 35 |
| SRF05/25 + FT015 | 25 | | 142 | 135 | 124 | 114 | 99 | 81 | 56 | 15 | 2.0 | 1.5 | 4.9 | 1516 | 836 | 680 | 39 |
| SRF05/30 + FT015 | 30 | | 171 | 161 | 149 | 136 | 119 | 97 | 67 | 18 | 2.0 | 1.5 | 4.9 | 1641 | 961 | 680 | 41 |
| SRF05/35 + FT022 | 35 | | 199 | 188 | 174 | 159 | 138 | 113 | 78 | 21 | 3.0 | 2.2 | 7.0 | 1816 | 1086 | 730 | 45 |
| SRF05/40 + FT022 | 40 | | 228 | 215 | 199 | 182 | 158 | 129 | 89 | 24 | 3.0 | 2.2 | 7.0 | 1941 | 1211 | 730 | 47 |
| SRF05/45 + FT022 | 45 | | 256 | 242 | 224 | 204 | 178 | 145 | 100 | 27 | 3.0 | 2.2 | 7.0 | 2066 | 1336 | 730 | 49 |
| SRF05/50 + FT030 | 50 | | 285 | 269 | 249 | 227 | 198 | 162 | 111 | 31 | 4.0 | 3.0 | 9.2 | 2231 | 1461 | 770 | 52 |
| SRF05/55 + FT030 | 55 | | 313 | 296 | 273 | 250 | 217 | 178 | 122 | 34 | 4.0 | 3.0 | 9.2 | 2356 | 1586 | 770 | 54 |
| SRF05/60 + FT030 | 60 | | 341 | 323 | 298 | 272 | 237 | 194 | 133 | 37 | 4.0 | 3.0 | 9.2 | 2481 | 1711 | 770 | 56 |

Pump Delivery Size :- Standard : 1¼" BSP (32 mm)

Note:- Intermediate stages available on Request



PERFORMANCE CHART FOR 4" BOREWELL SUBMERSIBLE PUMPSETS

50Hz

| PUMP + MOTOR | STAGES | CAPACITY | | | | | | | | POWER | | RATED CURRENT (A) | DIMENSIONS in 'mm' | | | APPROX. PUMPSET WEIGHT | |
|----------------------|--------|----------|-----|------|-----|-----|-----|-----|-----|-------|------|-------------------|--------------------|------|------|------------------------|----|
| | | UK gpm | 0 | 3 | 6 | 8 | 11 | 13 | 15 | | | | 17 | Max | | | |
| | | lpm | 0 | 13 | 25 | 38 | 50 | 58 | 67 | 75 | HP | | kW | A | B | C | Kg |
| | | lps | 0 | 0.2 | 0.4 | 0.6 | 0.8 | 1.0 | 1.1 | 1.3 | | | | | | | |
| m ³ /hr | 0 | 0.75 | 1.5 | 2.25 | 3.0 | 3.5 | 4.0 | 4.5 | | | | | | | | | |
| SINGLE PHASE - 220 V | | | | | | | | | | | | | | | | | |
| SRF08/05 + FS003 | 05 | HEAD (m) | 30 | 28 | 27 | 24 | 20 | 16 | 11 | 5 | 0.5 | 0.37 | 5.0 | 876 | 336 | 540 | 26 |
| SRF08/08 + FS005 | 08 | | 47 | 45 | 42 | 39 | 32 | 26 | 18 | 9 | 0.75 | 0.55 | 6.0 | 981 | 411 | 570 | 28 |
| SRF08/11 + FS007 | 11 | | 65 | 62 | 58 | 53 | 44 | 36 | 25 | 12 | 1.0 | 0.75 | 7.0 | 1086 | 486 | 600 | 30 |
| SRF08/16 + FS011 | 16 | | 95 | 90 | 85 | 77 | 64 | 52 | 36 | 17 | 1.5 | 1.1 | 10.0 | 1251 | 611 | 640 | 34 |
| SRF08/22 + FS015 | 22 | | 130 | 124 | 117 | 106 | 88 | 71 | 50 | 24 | 2.0 | 1.5 | 13.8 | 1441 | 761 | 680 | 38 |
| SRF08/30 + FS022 | 30 | | 178 | 169 | 159 | 145 | 120 | 97 | 68 | 32 | 3.0 | 2.2 | 19.8 | 1691 | 961 | 730 | 43 |
| SRF08/34 + FS022 | 34 | | 201 | 192 | 181 | 164 | 136 | 110 | 77 | 37 | 3.0 | 2.2 | 19.8 | 1791 | 1061 | 730 | 45 |
| SRF08/55 + FS037 | 55 | | 326 | 310 | 292 | 265 | 221 | 178 | 124 | 59 | 5.0 | 3.7 | 27.0 | 2458 | 1586 | 872 | 56 |
| THREE PHASE - 380 V | | | | | | | | | | | | | | | | | |
| SRF08/11 + FT007 | 11 | HEAD (m) | 65 | 62 | 58 | 53 | 44 | 36 | 25 | 12 | 1.0 | 0.75 | 2.7 | 1086 | 486 | 600 | 30 |
| SRF08/16 + FT011 | 16 | | 95 | 90 | 85 | 77 | 64 | 52 | 36 | 17 | 1.5 | 1.1 | 3.5 | 1231 | 611 | 620 | 33 |
| SRF08/22 + FT015 | 22 | | 130 | 124 | 117 | 106 | 88 | 71 | 50 | 24 | 2.0 | 1.5 | 4.9 | 1441 | 761 | 680 | 38 |
| SRF08/30 + FT022 | 30 | | 178 | 169 | 159 | 145 | 120 | 97 | 68 | 32 | 3.0 | 2.2 | 7.0 | 1691 | 961 | 730 | 43 |
| SRF08/34 + FT022 | 34 | | 201 | 192 | 181 | 164 | 136 | 110 | 77 | 37 | 3.0 | 2.2 | 7.0 | 1791 | 1061 | 730 | 45 |
| SRF08/40 + FT030 | 40 | | 237 | 226 | 212 | 193 | 160 | 130 | 90 | 43 | 4.0 | 3.0 | 9.2 | 1981 | 1211 | 770 | 48 |
| SRF08/45 + FT030 | 45 | | 266 | 254 | 239 | 217 | 180 | 146 | 102 | 49 | 4.0 | 3.0 | 9.2 | 2106 | 1336 | 770 | 50 |
| SRF08/55 + FT037 | 55 | | 326 | 310 | 292 | 265 | 221 | 178 | 124 | 59 | 5.0 | 3.7 | 10.9 | 2458 | 1586 | 872 | 56 |

Pump Delivery Size :- Standard : 1¼" BSP (32 mm)

Note:- Intermediate stages available on Request




PERFORMANCE CHART FOR 4" BOREWELL SUBMERSIBLE PUMPSETS

50Hz

| PUMP + MOTOR | STAGES | CAPACITY | | | | | | | | POWER | | RATED CURRENT (A) | DIMENSIONS in 'mm' | | | APPROX. PUMP SET WEIGHT | |
|----------------------|--------|--------------------|-----|-----|-----|-----|-----|-----|-----|-------|------|-------------------|--------------------|------|------|-------------------------|----|
| | | UK gpm | 0 | 3 | 7 | 10 | 13 | 16 | 19 | | | | 20 | Max | | | |
| | | lpm | 0 | 15 | 30 | 45 | 60 | 73 | 87 | 92 | HP | | kW | A | B | C | Kg |
| | | lps | 0 | 0.3 | 0.5 | 0.8 | 1.0 | 1.2 | 1.4 | 1.5 | | | | | | | |
| | | m ³ /hr | 0 | 0.9 | 1.8 | 2.7 | 3.6 | 4.4 | 5.2 | 5.5 | | | | | | | |
| SINGLE PHASE - 220 V | | | | | | | | | | | | | | | | | |
| SRF10/04 + FS003 | 04 | HEAD (m) | 24 | 23 | 22 | 20 | 18 | 14 | 8 | 6 | 0.5 | 0.37 | 5.0 | 851 | 311 | 540 | 25 |
| SRF10/07 + FS005 | 07 | | 42 | 40 | 38 | 35 | 31 | 24 | 15 | 11 | 0.75 | 0.55 | 6.0 | 956 | 386 | 570 | 27 |
| SRF10/10 + FS007 | 10 | | 60 | 57 | 54 | 50 | 44 | 34 | 21 | 16 | 1.0 | 0.75 | 7.0 | 1061 | 461 | 600 | 30 |
| SRF10/15 + FS011 | 15 | | 90 | 85 | 81 | 75 | 66 | 51 | 32 | 24 | 1.5 | 1.1 | 10.0 | 1226 | 586 | 640 | 33 |
| SRF10/20 + FS015 | 20 | | 119 | 114 | 108 | 101 | 89 | 68 | 42 | 32 | 2.0 | 1.5 | 13.8 | 1391 | 711 | 680 | 37 |
| SRF10/25 + FS022 | 25 | | 149 | 142 | 135 | 126 | 111 | 85 | 53 | 40 | 3.0 | 2.2 | 19.8 | 1566 | 836 | 730 | 41 |
| SRF10/30 + FS022 | 30 | | 179 | 171 | 162 | 151 | 133 | 102 | 64 | 48 | 3.0 | 2.2 | 19.8 | 1691 | 961 | 730 | 43 |
| SRF10/45 + FS037 | 45 | | 269 | 256 | 243 | 226 | 199 | 153 | 95 | 72 | 5.0 | 3.7 | 27.0 | 2208 | 1336 | 872 | 52 |
| SRF10/65 + FS056 | 65 | | 388 | 370 | 351 | 327 | 288 | 222 | 138 | 104 | 7.5 | 5.5 | 35.0 | 2818 | 1836 | 982 | 65 |
| SRF10/70 + FS056 | 70 | | 418 | 398 | 378 | 352 | 310 | 239 | 148 | 112 | 7.5 | 5.5 | 35.0 | 2943 | 1961 | 982 | 67 |
| SRF10/75 + FS056 | 75 | 448 | 427 | 405 | 377 | 332 | 256 | 159 | 120 | 7.5 | 5.5 | 35.0 | 3068 | 2086 | 982 | 69 | |
| THREE PHASE - 380 V | | | | | | | | | | | | | | | | | |
| SRF10/10 + FT007 | 10 | HEAD (m) | 60 | 57 | 54 | 50 | 44 | 34 | 21 | 16 | 1.0 | 0.75 | 2.7 | 1061 | 461 | 600 | 30 |
| SRF10/15 + FT011 | 15 | | 90 | 85 | 81 | 75 | 66 | 51 | 32 | 24 | 1.5 | 1.1 | 3.5 | 1206 | 586 | 620 | 32 |
| SRF10/20 + FT015 | 20 | | 119 | 114 | 108 | 101 | 89 | 68 | 42 | 32 | 2.0 | 1.5 | 4.9 | 1391 | 711 | 680 | 37 |
| SRF10/25 + FT022 | 25 | | 149 | 142 | 135 | 126 | 111 | 85 | 53 | 40 | 3.0 | 2.2 | 7.0 | 1566 | 836 | 730 | 41 |
| SRF10/30 + FT022 | 30 | | 179 | 171 | 162 | 151 | 133 | 102 | 64 | 48 | 3.0 | 2.2 | 7.0 | 1691 | 961 | 730 | 43 |
| SRF10/35 + FT030 | 35 | | 209 | 199 | 189 | 176 | 155 | 119 | 74 | 56 | 4.0 | 3.0 | 9.2 | 1856 | 1086 | 770 | 47 |
| SRF10/40 + FT030 | 40 | | 239 | 228 | 216 | 201 | 177 | 136 | 85 | 64 | 4.0 | 3.0 | 9.2 | 1981 | 1211 | 770 | 48 |
| SRF10/45 + FT037 | 45 | | 269 | 256 | 243 | 226 | 199 | 153 | 95 | 72 | 5.0 | 3.7 | 10.9 | 2208 | 1336 | 872 | 52 |
| SRF10/50 + FT037 | 50 | | 299 | 285 | 270 | 252 | 222 | 171 | 106 | 80 | 5.0 | 3.7 | 10.9 | 2333 | 1461 | 872 | 54 |
| SRF10/55 + FT045 | 55 | | 328 | 313 | 297 | 277 | 244 | 188 | 117 | 88 | 6.0 | 4.5 | 13.1 | 2508 | 1586 | 922 | 59 |
| SRF10/60 + FT045 | 60 | | 358 | 341 | 324 | 302 | 266 | 205 | 127 | 96 | 6.0 | 4.5 | 13.1 | 2633 | 1711 | 922 | 61 |
| SRF10/65 + FT056 | 65 | | 388 | 370 | 351 | 327 | 288 | 222 | 138 | 104 | 7.5 | 5.5 | 15.8 | 2818 | 1836 | 982 | 65 |
| SRF10/70 + FT056 | 70 | | 418 | 398 | 378 | 352 | 310 | 239 | 148 | 112 | 7.5 | 5.5 | 15.8 | 2943 | 1961 | 982 | 67 |
| SRF10/75 + FT056 | 75 | | 448 | 427 | 405 | 377 | 332 | 256 | 159 | 120 | 7.5 | 5.5 | 15.8 | 3068 | 2086 | 982 | 69 |

Pump Delivery Size :- Standard : 1¼" BSP (32 mm)

Note:- Intermediate stages available on Request

|  | | PERFORMANCE CHART FOR 4" BOREWELL SUBMERSIBLE PUMPSETS | | | | | | | | | | | 50Hz | | | | |
|--|--------|---|-----|-----|-----|-----|-----|-----|-----|-----|-------|------|-------------------|--------------------|------|-----|-------------------------|
| PUMP + MOTOR | STAGES | CAPACITY | | | | | | | | | POWER | | RATED CURRENT (A) | DIMENSIONS in 'mm' | | | APPROX. PUMP SET WEIGHT |
| | | UK gpm | 0 | 7 | 11 | 15 | 18 | 22 | 26 | 29 | | | | Max | | | |
| | | lpm | 0 | 33 | 50 | 67 | 83 | 100 | 117 | 133 | A | B | | C | Kg | | |
| | | lps | 0 | 0.6 | 0.8 | 1.1 | 1.4 | 1.7 | 1.9 | 2.2 | | | | | | | |
| m ³ /hr | 0 | 2.0 | 3.0 | 4.0 | 5.0 | 6.0 | 7.0 | 8.0 | HP | kW | | | | | | | |
| SINGLE PHASE - 220 V | | | | | | | | | | | | | | | | | |
| SRF14/05 + FS005 | 05 | HEAD (m) | 29 | 26 | 24 | 22 | 20 | 18 | 15 | 12 | 0.75 | 0.55 | 6.0 | 975 | 405 | 570 | 27 |
| SRF14/07 + FS007 | 07 | | 40 | 37 | 34 | 31 | 28 | 25 | 22 | 17 | 1.0 | 0.75 | 7.0 | 1082 | 482 | 600 | 30 |
| SRF14/10 + FS011 | 10 | | 58 | 52 | 48 | 44 | 40 | 36 | 31 | 24 | 1.5 | 1.1 | 10.0 | 1237 | 597 | 640 | 33 |
| SRF14/14 + FS015 | 14 | | 81 | 73 | 67 | 62 | 56 | 51 | 43 | 33 | 2.0 | 1.5 | 13.8 | 1431 | 751 | 680 | 36 |
| SRF14/18 + FS022 | 18 | | 104 | 94 | 86 | 79 | 72 | 65 | 56 | 43 | 3.0 | 2.2 | 19.8 | 1635 | 905 | 730 | 41 |
| SRF14/21 + FS022 | 21 | | 121 | 110 | 101 | 92 | 84 | 76 | 65 | 50 | 3.0 | 2.2 | 19.8 | 1751 | 1021 | 730 | 42 |
| SRF14/32 + FS037 | 32 | | 185 | 167 | 153 | 141 | 128 | 116 | 99 | 76 | 5.0 | 3.7 | 27.0 | 2316 | 1444 | 872 | 52 |
| SRF14/35 + FS037 | 35 | | 202 | 183 | 168 | 154 | 140 | 127 | 108 | 83 | 5.0 | 3.7 | 27.0 | 2432 | 1560 | 872 | 53 |
| SRF14/37 + FS037 | 37 | | 214 | 193 | 177 | 163 | 148 | 134 | 114 | 88 | 5.0 | 3.7 | 27.0 | 2509 | 1637 | 872 | 54 |
| SRF14/47 + FS056 | 47 | | 272 | 245 | 225 | 207 | 188 | 170 | 145 | 111 | 7.5 | 5.5 | 35.0 | 3004 | 2022 | 982 | 65 |
| SRF14/52 + FS056 | 52 | | 301 | 271 | 249 | 229 | 209 | 188 | 161 | 123 | 7.5 | 5.5 | 35.0 | 3196 | 2214 | 982 | 67 |
| SRF14/54 + FS056 | 54 | | 312 | 282 | 259 | 238 | 217 | 195 | 167 | 128 | 7.5 | 5.5 | 35.0 | 3273 | 2291 | 982 | 68 |
| THREE PHASE - 380 V | | | | | | | | | | | | | | | | | |
| SRF14/07 + FT007 | 07 | HEAD (m) | 40 | 37 | 34 | 31 | 28 | 25 | 22 | 17 | 1.0 | 0.75 | 2.7 | 1082 | 482 | 600 | 30 |
| SRF14/10 + FT011 | 10 | | 58 | 52 | 48 | 44 | 40 | 36 | 31 | 24 | 1.5 | 1.1 | 3.5 | 1217 | 597 | 620 | 32 |
| SRF14/14 + FT015 | 14 | | 81 | 73 | 67 | 62 | 56 | 51 | 43 | 33 | 2.0 | 1.5 | 4.9 | 1431 | 751 | 680 | 36 |
| SRF14/18 + FT022 | 18 | | 104 | 94 | 86 | 79 | 72 | 65 | 56 | 43 | 3.0 | 2.2 | 7.0 | 1635 | 905 | 730 | 41 |
| SRF14/21 + FT022 | 21 | | 121 | 110 | 101 | 92 | 84 | 76 | 65 | 50 | 3.0 | 2.2 | 7.0 | 1751 | 1021 | 730 | 42 |
| SRF14/25 + FT030 | 25 | | 145 | 131 | 120 | 110 | 100 | 91 | 77 | 59 | 4.0 | 3.0 | 9.2 | 1945 | 1175 | 770 | 46 |
| SRF14/28 + FT030 | 28 | | 162 | 146 | 134 | 123 | 112 | 101 | 87 | 66 | 4.0 | 3.0 | 9.2 | 2060 | 1290 | 770 | 48 |
| SRF14/32 + FT037 | 32 | | 185 | 167 | 153 | 141 | 128 | 116 | 99 | 76 | 5.0 | 3.7 | 10.9 | 2316 | 1444 | 872 | 52 |
| SRF14/35 + FT037 | 35 | | 202 | 183 | 168 | 154 | 140 | 127 | 108 | 83 | 5.0 | 3.7 | 10.9 | 2432 | 1560 | 872 | 53 |
| SRF14/37 + FT037 | 37 | | 214 | 193 | 177 | 163 | 148 | 134 | 114 | 88 | 5.0 | 3.7 | 10.9 | 2509 | 1637 | 872 | 54 |
| SRF14/38 + FT045 | 38 | | 220 | 198 | 182 | 167 | 152 | 138 | 117 | 90 | 6.0 | 4.5 | 13.1 | 2597 | 1675 | 922 | 57 |
| SRF14/42 + FT045 | 42 | | 243 | 219 | 201 | 185 | 168 | 152 | 130 | 100 | 6.0 | 4.5 | 13.1 | 2751 | 1829 | 922 | 59 |
| SRF14/45 + FT045 | 45 | | 260 | 235 | 216 | 198 | 180 | 163 | 139 | 107 | 6.0 | 4.5 | 13.1 | 2867 | 1945 | 922 | 61 |
| SRF14/47 + FT056 | 47 | | 272 | 245 | 225 | 207 | 188 | 170 | 145 | 111 | 7.5 | 5.5 | 15.8 | 3004 | 2022 | 982 | 65 |
| SRF14/52 + FT056 | 52 | | 301 | 271 | 249 | 229 | 209 | 188 | 161 | 123 | 7.5 | 5.5 | 15.8 | 3196 | 2214 | 982 | 67 |
| SRF14/54 + FT056 | 54 | 312 | 282 | 259 | 238 | 217 | 195 | 167 | 128 | 7.5 | 5.5 | 15.8 | 3273 | 2291 | 982 | 68 | |

Pump Delivery Size :- Standard : 1½" BSP (40 mm)

Note:- Intermediate stages available on Request



PERFORMANCE CHART FOR 4" BOREWELL SUBMERSIBLE PUMPSETS

50Hz

| PUMP + MOTOR | STAGES | CAPACITY | | | | | | | | | POWER | | RATED CURRENT (A) | DIMENSIONS in 'mm' Max | | | APPROX. PUMP SET WEIGHT |
|----------------------|--------|--------------------|-----|-----|-----|-----|-----|-----|------|------|-------|------|-------------------|---------------------------|------|-----|-------------------------------|
| | | UK gpm | 0 | 7 | 15 | 22 | 29 | 35 | 41 | 47 | | | | | | | |
| | | lpm | 0 | 33 | 67 | 100 | 133 | 160 | 187 | 213 | | | | | | | |
| | | lps | 0 | 0.6 | 1.1 | 1.7 | 2.2 | 2.7 | 3.1 | 3.6 | | | | | | | |
| | | m ³ /hr | 0 | 2.0 | 4.0 | 6.0 | 8.0 | 9.6 | 11.2 | 12.8 | HP | kW | | | | Kg | |
| SINGLE PHASE - 220 V | | | | | | | | | | | | | | | | | |
| SRF22/05 + FS007 | 05 | HEAD (m) | 28 | 27 | 25 | 22 | 20 | 16 | 12 | 6 | 1.0 | 0.75 | 7.0 | 1022 | 422 | 600 | 29 |
| SRF22/07 + FS011 | 07 | | 40 | 37 | 35 | 31 | 28 | 23 | 16 | 9 | 1.5 | 1.1 | 10.0 | 1146 | 506 | 640 | 31 |
| SRF22/10 + FS015 | 10 | | 57 | 53 | 50 | 44 | 40 | 33 | 23 | 13 | 2.0 | 1.5 | 13.8 | 1312 | 632 | 680 | 34 |
| SRF22/15 + FS022 | 15 | | 85 | 80 | 75 | 66 | 60 | 49 | 35 | 19 | 3.0 | 2.2 | 19.8 | 1572 | 842 | 730 | 39 |
| SRF22/25 + FS037 | 25 | | 141 | 133 | 124 | 110 | 100 | 82 | 58 | 32 | 5.0 | 3.7 | 27.0 | 2134 | 1262 | 872 | 48 |
| SRF22/35 + FS056 | 35 | | 198 | 186 | 174 | 154 | 139 | 114 | 82 | 44 | 7.5 | 5.5 | 35.0 | 2664 | 1682 | 982 | 58 |
| SRF22/37 + FS056 | 37 | | 209 | 197 | 184 | 162 | 147 | 121 | 86 | 47 | 7.5 | 5.5 | 35.0 | 2748 | 1766 | 982 | 59 |
| THREE PHASE - 380 V | | | | | | | | | | | | | | | | | |
| SRF22/05 + FT007 | 05 | HEAD (m) | 28 | 27 | 25 | 22 | 20 | 16 | 12 | 6 | 1.0 | 0.75 | 2.7 | 1022 | 422 | 600 | 29 |
| SRF22/07 + FT011 | 07 | | 40 | 37 | 35 | 31 | 28 | 23 | 16 | 9 | 1.5 | 1.1 | 3.5 | 1126 | 506 | 620 | 30 |
| SRF22/10 + FT015 | 10 | | 57 | 53 | 50 | 44 | 40 | 33 | 23 | 13 | 2.0 | 1.5 | 4.9 | 1312 | 632 | 680 | 34 |
| SRF22/15 + FT022 | 15 | | 85 | 80 | 75 | 66 | 60 | 49 | 35 | 19 | 3.0 | 2.2 | 7.0 | 1572 | 842 | 730 | 39 |
| SRF22/20 + FT030 | 20 | | 113 | 106 | 99 | 88 | 80 | 65 | 47 | 25 | 4.0 | 3.0 | 9.2 | 1822 | 1052 | 770 | 43 |
| SRF22/25 + FT037 | 25 | | 141 | 133 | 124 | 110 | 100 | 82 | 58 | 32 | 5.0 | 3.7 | 10.9 | 2134 | 1262 | 872 | 48 |
| SRF22/30 + FT045 | 30 | | 170 | 160 | 149 | 132 | 119 | 98 | 70 | 38 | 6.0 | 4.5 | 13.1 | 2394 | 1472 | 922 | 53 |
| SRF22/35 + FT056 | 35 | | 198 | 186 | 174 | 154 | 139 | 114 | 82 | 44 | 7.5 | 5.5 | 15.8 | 2664 | 1682 | 982 | 58 |
| SRF22/37 + FT056 | 37 | | 209 | 197 | 184 | 162 | 147 | 121 | 86 | 47 | 7.5 | 5.5 | 15.8 | 2748 | 1766 | 982 | 59 |

Pump Delivery Size :- Standard : 2" BSP (50 mm)

Note:- Intermediate stages available on Request